ODSIF

How to setup TAKE10 to contol ODSIF LED Lightthemes lamps

21. May, 2011

Content

I	<u>Page.</u>
1.0 Default X10 settings for ODSIF LED Theme lamps	1
1.1 How to adjust Take 10 to control ODSIF LED theme lamps	1

1.0 DEFAULT X10 SETTINGS FOR ODSIF LED THEME LAMPS

Odsif LED light themes lamps default settings are following:

B1 ON – Turn light on

B1 OFF – Turn light off

B2 ON - Change to next theme

B2 OFF – Change to previous theme

1.1 How to adjust Take 10 to control ODSIF LED theme lamps

Do following to set the remote to change themes.

- 1. Select setup from the home screen
- 2. Select X10 from the Setup screen
- 3. Select Add/Edit from the Setup X10 screen
- 4. Select which room you have install your ODSIF lamps I.e. "Living Room"
- 5. In the screen "Let's add an X10 device press "OK"
- 6. Select label
- 7. Choose label by your choose
- 8. Select Address
- 9. Choose B2 as an address for the Device
- 10. Select Pick Logo
- 11. Pick a logo by your choose
- 12. Select Pick Device
- 13. Select Lamps from the Pick Device Screen
- 14. Select LM12 Plug in Lamp Module
- 15. Select Done

Repeat the above with B1 as an address in order to control On/Off functionality.

Now you can change theme by doing following:

- 1. Select X10 from the Pick Module Screen
- 2. Select the room you have choosen above
- 3. Select the Label you have choosen above
- 4. Use CH/P + for changing to the next theme
- 5. Use CH/P for changing to the previous theme

Now you can turn the lamps on/off by doing following:

- 6. Select X10 from the Pick Module Screen
- 7. Select the room you have choosen above
- 8. Select the Label you have choosen above

- 9. Use CH/P + for turning the lamps on 10. Use CH/P for turning the lamps off